

Photoelectric lighting controller

# NightMatic 2000

EAN 4007841550417



## Functional description

It's thundering outside and getting dark. You're sitting snugly in the living-room, waiting for your guests. Who'd want to go out and turn the outside light on? The NightMatic 2000 reliably does this for you – whether it's raining, snowing, blowing a gale or you simply have something better to do. Of course, the light-level threshold at which the sensor responds and turns the light 'ON' is defined by no other than you yourself.

## Technical specifications

<b>Dimensions(w x h x d):</b>	99 x 74 x 37 mm
<b>Voltage</b>	230-240 V/50 Hz
<b>Type</b>	Photoelectric lighting controller
<b>Application</b>	Outdoors
<b>Installation</b>	Wall
<b>max. output (resistive load, incandescent lamp)</b>	1000 W
<b>max. output (uncorrected, inductive, <math>\cos \varphi = 0.5</math>, e.g. fluorescent lamps)</b>	500 VA
<b>Response brightness:</b>	approx. 2 - 10 lx
<b>Output</b>	Max. 1000 W, max. 4 fluorescent lamps / LED lamps, C < 88 $\mu$ F
<b>Power consumption</b>	< 0.8 W
<b>Version</b>	White
<b>IP rating</b>	IP54
<b>Protection class</b>	II