


Photoelectric lighting controller

NightMatic 3000 Vario

EAN 4007841550516



Functional description

Did I turn the light 'OFF'? Or did I forget to? With the NightMatic 3000 Vario, this question's not an issue any more. When it's dark it takes care of switching the outside light 'ON' and 'OFF' all by itself. But that's not all: The intelligent night-economy mode automatically switches the light 'OFF' after a programmable time and back 'ON' again in the early hours between 4 and 5 o'clock. The photo-cell controller feels most at home on your property, on the front of a building or in a shop window.

Technical specifications

Dimensions(w x h x d):	99 x 74 x 37 mm
Voltage	230-240 V/50 Hz
Type	Photoelectric lighting controller
Application	Outdoors
Installation	Wall
Response brightness:	approx. 0.5 – 10 lux /at press of button
Output	Max. 1000 W, max. 4 fluorescent lamps / LED lamps, C < 88 µF
Night economy mode	variable night 'OFF' time
Power consumption	< 0.8 W
Version	Black
IP rating	IP54
Protection class	II